



# RF EP-DIMMER-1Z DIAL CONTROLLER

EP-2805R-DIMMER-1Z

EP-2805D-DIMMER-1Z

## RF LED RGB Controller EP-2805-DIMMER-1Z 1 Zone Dimmer

- Reliable & stable switch and dimming control function, control range  $\geq 20M$
- Battery in the remote is with long life span. It normally can use for 5 years.
- Switch on/off of lightings slowly, without any flash, meet the comfort of human eyes.
- Dimming range 0.1-100%.
- Use with power repeater to expand the output power unlimitedly.
- 256 levels logarithmic dimming, ideal for human eye sensitivity to lighting, dimming smoothly without any flash.
- Enable to control 1 zone
- Rotary adjustment, simple and friendly-use.

### SPECIFICATIONS

REMOTE: (MODEL: EP-2805R & EP-2805D)

Operation voltage: 3VDC (CR2032 & CR2025)

Operation frequency: 434MHZ/868MHZ

RECEIVER: (MODEL: EP-2501-EA-1Z-CVC)

Input Voltage: 12-24VDC

Input Current: 4CH  $\times$  8A max

Output power: 4CH  $\times$  (36-108W) max

Working Frequency: 434MHZ/868MHZ/915MHZ (optional)



# EPIC™ GLOBAL SYSTEM

BEYOND THE LIMITS!