

| |
|----------------------------------|
| Specifier's Reference |
| Project |
| Type |
| Model No. |
| Comments or Special Instructions |

EPIC'S EP-MEDIA2 DMX CONTROLLERS

The EP-MEDIA2-BC is the budget product in the range. It comes with the Sunlite Suite 2 software in Economy mode and offers 512 DMX OUT and 512 DMX IN channels. This is the ideal product for applications where a single DMX universe is enough (clubs, djs, bars...). Associated to a MIDI console, the software becomes very powerful and offers all you need to control your lighting.



Specifications

- Standard USB-DMX interface.
- 1 DMX OUT universe (512 channels) and 1 DMX IN universe
- Works with Easy Sand Alone, Sunlite Suite 1 and Suite 2 software (not compatible with EasyShow, ESA Pro).
- Delivered with an installation CDROM including user manual.
- Compatible with Windows XP/VISTA/SEVEN 32/64-bit.

| | | EP-MEDIA2-BC Basic Class | EP-MEDIA2-EC Economy Class | EP-MEDIA2-FC First Class | EP-MEDIA2-FC+ First Class + |
|------------------|-----------------------------|-----------------------------|-------------------------------|-----------------------------|--------------------------------|
| LIVE USE WITH PC | DMX channels | 512(IN) 512(OUT) | 2x512 | 3x512 | 3x512 |
| | Ethernet channels (Art-Net) | | 2x512 | 4x512 | Unlimited |
| | Easy View | Limited | Limited | Full | Full |
| | Easy Show | | | • | • |
| | MIDI live control | • | • | • | • |
| | MIDI TIME CODE (IN-OUT) | | | • | • |
| | PC clock triggering | | | • | • |
| STAND ALONE USE | PORTS triggering | | • | • | • |
| | DMX channels | | 512 | 2x512 | 2x512 |
| | Infrared Remote Control | | | • | • |
| | Stand Alone memory | | 64K | miniSD | miniSD |
| | PORTS triggering | | • | • | • |
| | Clock/calendar triggering | | • | • | • |
| | Multi-zone | | | • | • |
| | Easy Stand Alone | | • | • | • |
| ESA PRO | | | • | • | |

Ordering Information

PRODUCT

- EP-MEDIA2-BC
 EP-MEDIA2-EC
 EP-MEDIA2-FC
 EP-MEDIA2-FC+

